

- ◆ **MODEL No.: GSR-N986\N987\N982**
- ◆ **Category: DVB-S FTA RECEIVER SD**



Main Features:

- ✓ Max. 2000 channels receivable.
- ✓ Channel list mode in All, Favorite, Satellite. Finding channels by name.
- ✓ 5 Favorite channel groups (Max. 100 channels in each group). Channel search in automatic and manual. Channel Sorting by channel number, Alphabet, FTA. Installation Wizard helps easy and automatic installation step by step.
- ✓ DiSEqC Control version 1.0 and 1.2 compatible.
- ✓ Timer Setting Supports automatic Turn-Off daily
- ✓ PAL/NTSC In and Out.
- ✓ English、French、Russian、Arabic、Farsi、Portuguese、Turkish、Thai OSD Languages.
- ✓ Serial connection (RS-232).
- ✓ Extended information shows the full program information.
- ✓ Parental lock function for menu and selectable per channel.
- ✓ Supports Games, caculator.

Technical specification

◆ **Chipset and Memory:**

CPU **ALI M3329**

Flash: 4Mbit

SDRAM: 16Mbit

◆ **Power:**

Input power: AC 90 ~ 240V, 50/60 Hz

Maximum power consumption: 15W

◆ **Interface:**

RF signal input: x1
Video output: RCA x1
Audio output: Stereo RCA x1
RS-232 4 Pin\DB9M(Optional)
Baud Rate 115Kbps

◆ **TUNER****Tuner: RDA5815M**

Receiving Frequency: 950 ~ 2150 MHz

◆ **RF Modulator**

Picture Carrier Frequency: 209.25 MHz
Output Channel: VHF CH11/CH21~CH69(Optional N982)
Color system: PAL B/G/I/D/K and NTSC M

◆ **Video Decoding**

Compliant with: MPEG-2 ISO/IEC 13818
MPEG-2 MP @ ML
Max 5Mbit/s

Aspect ratio: 4:3

Video format: PAL / NTSC

Resolution: PAL: 720 x 576
NTSC: 720 x 480

◆ **Audio Decoding**

Compliant with: MPEG-1/2
Sampling Frequency: 32/44.1/48KHz